3. Electrical Parts List

Location no.	Code no.	Description & Specification	Remarks
	3301-000132	CORE-FERRITE;AC,28.8x19.3x7.5mm,1400,290	
	3809-001224	CABLE-FLAT;30V,80C,80mm,13P,1.25mm,UL289	
	3809-001573	FPC CABLE-FLAT;30V,80C,270MM,20P,1.25MM,	
	3809-001574	FPC CABLE-FLAT;30V,80C,100MM,26P,1.25MM,	
	3809-001578	FPC CABLE-FLAT;30V,80C,170mm,20P,1mm,UL2	
	3809-001582	CABLE-FLAT;30V,80,130mm,20P,1mm,UL2896	
	AH31-00039B	MOTOR FAN;C151BK10A2430,RDM5015S,0.12A,-	
	AH39-00257F	POWER CORD;MAX980,-,CP2,250V,2.5A,1830MM	
	AH39-00618A	WIRE HARNESS;HT-DS700,-,-,8P,-,-,26AWG,P	
	AH39-40001Z	CBF CABLE;SJ03-09-206,-,2P-2P,2000MM,-,A	
	AH40-00076A	TUNER-PACK ASSY;KST-ML104FA1-52,FM/RDS,-	
	AH44-00042B	SMPS;HT-DS700,ORTP-923,AC/DC,600W,2	
	AH59-01354A	**DECK-MECHA ASSY;-,HT-DS400,-,14.4 MM,5 V**	
	AH31-00030B	MOTOR DC;-,RF-300E-1D390,-,-,-,-,-,-,	
	AH39-00425A	CONNECT WIRE;HT-DL200,RING,-,-,-,BLK,-,R	
	AH59-01184A	DECK-MECHA ASSY;-,CMS-SD100,-,-,-,-,CD D	
	AH30-00055A	PICK UP-DECK;SOH-DH11,-,0.60,1.71,-,CMS-	
	AH91-00005A	**ASSY DECK-DVD;-,-,CMS-SD100**	
	3302-001505	MAGNET-PERMENENT;AC,-,9800GAUSS,23MGOE,1	
	3409-001119	SWITCH-DETECTOR;5V DC,1.0A,DPST,30gf,-	
	3809-001451	CABLE-FLAT;30V,80C,60MM,24P,0.5MM,AWM206	
	AH92-02117A	**ASSY PCB;HT-DS400,ES6698FD,ES6603S**	
AD5	0401-001090	DIODE-SWITCHING;1SS355,80V,100MA,SOD-323	
AD3	0402-000309	DIODE-RECTIFIER;1SR154-400,400V,1A,SOD-1	
DZD1	0403-001062	DIODE-ZENER;UDZ4.7B,4.55-4.75V,200MW,SOD	
RD1	0407-000116	DIODE-ARRAY;DAP202K,80V,100mA,CK2-3,SOT-	
DD1	0407-000116	DIODE-ARRAY;DAP202K,80V,100mA,CK2-3,SOT-	
VQ6	0501-000314	TR-SMALL SIGNAL;KSA812,PNP,150mW,SOT-23,	
VQ5	0501-000314	TR-SMALL SIGNAL;KSA812,PNP,150mW,SOT-23,	
VQ4	0501-000314	TR-SMALL SIGNAL;KSA812,PNP,150mW,SOT-23,	
VQ3	0501-000314	TR-SMALL SIGNAL;KSA812,PNP,150mW,SOT-23,	
VQ2	0501-000314	TR-SMALL SIGNAL;KSA812,PNP,150mW,SOT-23,	
VQ1	0501-000314	TR-SMALL SIGNAL;KSA812,PNP,150mW,SOT-23,	
RQ6	0501-000314	TR-SMALL SIGNAL;KSA812,PNP,150mW,SOT-23,	
RQ5	0501-000632	TR-SMALL SIGNAL;2SB1197K,PNP,200mW,SOT-2	
RQ1	0501-000632	TR-SMALL SIGNAL;2SB1197K,PNP,200mW,SOT-2	
RQ7	0504-000128	TR-DIGITAL;-,NPN,200MW,22K/22K,SOT-23,TP	
RQ4	0504-000128	TR-DIGITAL;-,NPN,200MW,22K/22K,SOT-23,TP	
RQ3	0504-000128	TR-DIGITAL;-,NPN,200MW,22K/22K,SOT-23,TP	
RQ2	0504-000128	TR-DIGITAL;-,NPN,200MW,22K/22K,SOT-23,TP	
Q1	0504-000128	TR-DIGITAL;-,NPN,200MW,22K/22K,SOT-23,TP	
U17	0801-002518	IC-CMOS LOGIC;74LCX157,2-INPUT MULTIPLEX	
MIC1	0801-002683	IC-CMOS LOGIC;74HCT245,TRANSCEIVER,TSSOP	
OPIC2	0802-001007	IC-BICMOS LOGIC;74LCX244,BUFFER/LINE DRI	
OPIC3	0802-001025	IC-BICMOS LOGIC;74LCX374,D FILP-FLOP,TSS	
OPIC1	1001-001170	IC-AUDIO SWITCH;CS8415A-CZ,RECEIVER&DECO	
DIC1	1003-001450	IC-MOTOR DRIVER;BA5954FM,SOP,28P,300MIL,	
DRIC1	1003-001507	IC-MOTOR DRIVER;FAN8423D3TF,SSOPH-375SG2	
RIC2	1003-001508	IC-MOTOR DRIVER;FAN8082DTF,SOP,8P,200MIL	
MIC6	1103-001334	IC-EEPROM;K524A60X81,1KX8BIT,SOP,8P,5X4M	
MIC8	1105-001535	IC-DRAM;M12L128168A-7T,4X2MX16BIT,TSOP	
MIC3	1107-001452	IC-FLASH MEMORY;29L160,2Mx8/1Mx16,TSOP,4	
RIC3	1201-001842	IC-OP AMP;TL3472CD,SO,TP,8P,-,DUAL,-,PAL	
RIC1	1201-002059	IC-RF AMP;ES6603SF,LQFP,64P,10X10MM,SING	
REG1	1203-002425	IC-POSI.FIXED REG.;AP1117,SOT-223,3P,138	
REG4	1203-002935	IC-POSI.ADJUST REG.;AIC1117ACE,TO-252,3P	
REG3	1203-002935	IC-POSI.ADJUST REG.;AIC1117ACE,TO-252,3P	
MIC4	1204-002224	IC-PAL/NTSC DECODER;ES6698FD,PQFP,208P,2	
DR3	2007-000029	R-CHIP;0ohm,5%,1/8W,TP,2012	
MR38	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
MR32	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
MR26	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
MR25	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
MR53	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
MR96	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
RR27	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
RR29	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
DR41	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
DR53	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
DR57	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
DR61	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
MR22	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
FREE	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
DR8	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
DR65	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
PR17	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
PR21	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
PR22	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
PR16	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
PR15	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
PR14	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
RR31	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
PR27	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
PR26	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
PR25	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	

Location no.	Code no.	Description & Specification	Remarks
PR24	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
PR23	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
MR90	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
MR68	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
MR2	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
DR64	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
DR63	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
DR56	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
AR24	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
MR89	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
MR82	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
MR81	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
MR80	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
MR8	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
MR79	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
PR19	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
VR18	2007-000076	R-CHIP;330ohm,5%,1/10W,TP,1608	
VR19	2007-000076	R-CHIP;330ohm,5%,1/10W,TP,1608	
VR2	2007-000076	R-CHIP;330ohm,5%,1/10W,TP,1608	
VR3	2007-000076	R-CHIP;330ohm,5%,1/10W,TP,1608	
VR7	2007-000076	R-CHIP;330ohm,5%,1/10W,TP,1608	
VR8	2007-000076	R-CHIP;330ohm,5%,1/10W,TP,1608	
VR9	2007-000076	R-CHIP;330ohm,5%,1/10W,TP,1608	
VR17	2007-000076	R-CHIP;330ohm,5%,1/10W,TP,1608	
R105	2007-000076	R-CHIP;330ohm,5%,1/10W,TP,1608	
R106	2007-000076	R-CHIP;330ohm,5%,1/10W,TP,1608	
R107	2007-000076	R-CHIP;330ohm,5%,1/10W,TP,1608	
VR1	2007-000076	R-CHIP;330ohm,5%,1/10W,TP,1608	
VR12	2007-000076	R-CHIP;330ohm,5%,1/10W,TP,1608	
VR13	2007-000076	R-CHIP;330ohm,5%,1/10W,TP,1608	
VR14	2007-000076	R-CHIP;330ohm,5%,1/10W,TP,1608	
PR1	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	
PR18	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R55	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
RR32	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
RR34	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
RR35	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
RR37	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
MR50	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
DR28	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
DR35	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
DR38	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
MR49	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
MR3	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
MR1	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
AR25	2007-000081	R-CHIP;2.7Kohm,5%,1/10W,TP,1608	
MR17	2007-000082	R-CHIP;3.3Kohm,5%,1/10W,TP,1608	
MR16	2007-000082	R-CHIP;3.3Kohm,5%,1/10W,TP,1608	
MR11	2007-000082	R-CHIP;3.3Kohm,5%,1/10W,TP,1608	
MR10	2007-000082	R-CHIP;3.3Kohm,5%,1/10W,TP,1608	
DR20	2007-000082	R-CHIP;3.3Kohm,5%,1/10W,TP,1608	
R49	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
R50	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
RR1	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
RR2	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
DR44	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
DR59	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
MR94	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
R48	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
MR44	2007-000087	R-CHIP;6.8Kohm,5%,1/10W,TP,1608	
MR43	2007-000087	R-CHIP;6.8Kohm,5%,1/10W,TP,1608	
MR40	2007-000087	R-CHIP;6.8Kohm,5%,1/10W,TP,1608	
MR39	2007-000087	R-CHIP;6.8Kohm,5%,1/10W,TP,1608	
MR33	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
MR18	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
DR58	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
RR26	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
RR30	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
RR33	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
DR12	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
DR13	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
DR14	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
DR16	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
DR42	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
DR43	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
RR8	2007-000091	R-CHIP;12Kohm,5%,1/10W,TP,1608	
DR18	2007-000091	R-CHIP;12Kohm,5%,1/10W,TP,1608	
MR21	2007-000093	R-CHIP;20Kohm,5%,1/10W,TP,1608	
DR55	2007-000094	R-CHIP;22Kohm,5%,1/10W,TP,1608	
DR54	2007-000094	R-CHIP;22Kohm,5%,1/10W,TP,1608	
DR5	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
DR51	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
RR42	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
RR43	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
DR15	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
DR19	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
DR36	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
DR37	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
MR19	2007-000100	R-CHIP;68Kohm,5%,1/10W,TP,1608	

Location no.	Code no.	Description & Specification	Remarks
DR10	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	
DR60	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	
MR74	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	
RR39	2007-000109	R-CHIP;1Mohm,5%,1/10W,TP,1608	
MR67	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	
MR69	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	
MR71	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	
MR72	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	
MR73	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	
MR76	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	
MR77	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	
MR78	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	
R44	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	
DR17	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	
DR6	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	
MR45	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	
MR46	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	
MR47	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	
MR66	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	
MR60	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	
MR56	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	
MR55	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	
PR20	2007-000118	R-CHIP;390ohm,5%,1/10W,TP,1608	
MR20	2007-000118	R-CHIP;390ohm,5%,1/10W,TP,1608	
DR9	2007-000118	R-CHIP;390ohm,5%,1/10W,TP,1608	
DR33	2007-000118	R-CHIP;390ohm,5%,1/10W,TP,1608	
MR84	2007-000122	R-CHIP;1.2Kohm,5%,1/10W,TP,1608	
R58	2007-000122	R-CHIP;1.2Kohm,5%,1/10W,TP,1608	
RR10	2007-000122	R-CHIP;1.2Kohm,5%,1/10W,TP,1608	
RR12	2007-000122	R-CHIP;1.2Kohm,5%,1/10W,TP,1608	
MR31	2007-000122	R-CHIP;1.2Kohm,5%,1/10W,TP,1608	
MR12	2007-000122	R-CHIP;1.2Kohm,5%,1/10W,TP,1608	
MR13	2007-000122	R-CHIP;1.2Kohm,5%,1/10W,TP,1608	
MR14	2007-000122	R-CHIP;1.2Kohm,5%,1/10W,TP,1608	
MR15	2007-000122	R-CHIP;1.2Kohm,5%,1/10W,TP,1608	
DR49	2007-000123	R-CHIP;1.5Kohm,5%,1/10W,TP,1608	
DR50	2007-000123	R-CHIP;1.5Kohm,5%,1/10W,TP,1608	
MR30	2007-000134	R-CHIP;33Kohm,5%,1/10W,TP,1608	
RR28	2007-000308	R-CHIP;10ohm,5%,1/8W,TP,2012	
RR36	2007-000308	R-CHIP;10ohm,5%,1/8W,TP,2012	
PR1	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	
DR21	2007-000455	R-CHIP;18Kohm,1%,1/10W,TP,1608	
DR32	2007-000483	R-CHIP;1ohm,5%,1/8W,TP,2012	
DR31	2007-000483	R-CHIP;1ohm,5%,1/8W,TP,2012	
DR30	2007-000483	R-CHIP;1ohm,5%,1/8W,TP,2012	
DR1	2007-000483	R-CHIP;1ohm,5%,1/8W,TP,2012	
DR2	2007-000483	R-CHIP;1ohm,5%,1/8W,TP,2012	
DR29	2007-000483	R-CHIP;1ohm,5%,1/8W,TP,2012	
R45	2007-000608	R-CHIP;240ohm,5%,1/10W,TP,1608	
PR3	2007-000643	R-CHIP;270ohm,5%,1/10W,TP,1608	
RR38	2007-000694	R-CHIP;3.3ohm,5%,1/8W,TP,2012	
R4	2007-000694	R-CHIP;3.3ohm,5%,1/8W,TP,2012	
R5	2007-000799	R-CHIP;360ohm,5%,1/10W,TP,1608	
MR42	2007-000962	R-CHIP;5.1Kohm,1%,1/10W,TP,1608	
MR34	2007-000962	R-CHIP;5.1Kohm,1%,1/10W,TP,1608	
VR6	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	
VR5	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	
VR4	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	
VR11	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	
VR10	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	
RN3	2011-000651	R-NET;10OHM,5%,1/16W,L,CHIP,8P,TP,32	
RN2	2011-000651	R-NET;10OHM,5%,1/16W,L,CHIP,8P,TP,32	
RN1	2011-000651	R-NET;10OHM,5%,1/16W,L,CHIP,8P,TP,32	
DC12	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
DC11	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
RC9	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
RC4	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
RC25	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
RC2	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
R47	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C57	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
RC17	2203-000315	C-CER,CHIP;0.12NF,5%,50V,C0G,TP,1608	
RC23	2203-000357	C-CER,CHIP;0.15NF,5%,50V,C0G,TP,1608	
RC28	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,TP,1608,-	
RC26	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,TP,1608,-	
MC6	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,TP,1608,-	
MC3	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,TP,1608,-	
MC4	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,TP,1608,-	
MC5	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,TP,1608,-	
RC16	2203-000491	C-CER,CHIP;2.2nF,10%,50V,X7R,TP,1608,-	
RC14	2203-000491	C-CER,CHIP;2.2nF,10%,50V,X7R,TP,1608,-	
RC13	2203-000491	C-CER,CHIP;2.2nF,10%,50V,X7R,TP,1608,-	
RC12	2203-000491	C-CER,CHIP;2.2nF,10%,50V,X7R,TP,1608,-	
RC8	2203-000681	C-CER,CHIP;0.027NF,5%,50V,C0G,TP,1608	
MC50	2203-000681	C-CER,CHIP;0.027NF,5%,50V,C0G,TP,1608	
MC45	2203-000681	C-CER,CHIP;0.027NF,5%,50V,C0G,TP,1608	
MC44	2203-000681	C-CER,CHIP;0.027NF,5%,50V,C0G,TP,1608	
RC24	2203-000800	C-CER,CHIP;33nF,10%,25V,X7R,TP,1608	
MC8	2203-000888	C-CER,CHIP;4.7nF,10%,50V,X7R,TP,1608	
MC13	2203-000888	C-CER,CHIP;4.7nF,10%,50V,X7R,TP,1608	
DC13	2203-000888	C-CER,CHIP;4.7nF,10%,50V,X7R,TP,1608	
C59	2203-000888	C-CER,CHIP;4.7nF,10%,50V,X7R,TP,1608	
RC15	2203-000972	C-CER,CHIP;47nF,10%,16V,X7R,TP,1608	

Location no.	Code no.	Description & Specification	Remarks
MC25	2203-000972	C-CER,CHIP;47nF,10%,16V,X7R,TP,1608	
MC29	2203-000998	C-CER,CHIP;0.047NF,5%,50V,C0G,TP,1608	
MC37	2203-001052	C-CER,CHIP;0.56nF,10%,50V,X7R,TP,1608	
MC34	2203-001052	C-CER,CHIP;0.56nF,10%,50V,X7R,TP,1608	
MC27	2203-001052	C-CER,CHIP;0.56nF,10%,50V,X7R,TP,1608	
MC21	2203-001103	C-CER,CHIP;6.8nF,10%,50V,X7R,TP,1608,-	
RC6	2203-001222	C-CER,CHIP;0.82NF,10%,50V,X7R,TP,1608	
MC36	2203-001402	C-CER,CHIP;220nF,+80-20%,16V,Y5V,TP,1608	
RC22	2203-001402	C-CER,CHIP;220nF,+80-20%,16V,Y5V,TP,1608	
MC41	2203-001636	C-CER,CHIP;0.033nF,5%,50V,NP0,TP,1608	
MC40	2203-001636	C-CER,CHIP;0.033nF,5%,50V,NP0,TP,1608	
MC39	2203-001636	C-CER,CHIP;0.033nF,5%,50V,NP0,TP,1608	
RC5	2203-001656	C-CER,CHIP;0.47nF,5%,50V,NP0,TP,1608	
RC3	2203-001656	C-CER,CHIP;0.47nF,5%,50V,NP0,TP,1608	
C11	2203-001656	C-CER,CHIP;0.47nF,5%,50V,NP0,TP,1608	
MC18	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
MC17	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
MC16	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
MC15	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
MC19	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
MC2	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
MC26	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
MC28	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
MC30	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
DC9	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
DC1	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
DC10	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
DC14	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
DC15	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
DC16	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
DC17	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
DC6	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
DC7	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
DC8	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
MC31	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
PC18	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
PC8	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
PC9	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
RC1	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
RC11	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
RC18	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
RC43	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
RC44	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
RC7	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
PC17	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
MC38	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
MC47	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
MC48	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
MC7	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
PC12	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
PC13	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
PC14	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
PC15	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
PC16	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
BC19	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
BC2	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
BC20	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
BC21	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
BC22	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
BC23	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
BC24	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
BC25	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
BC26	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
BC18	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
BC1	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
BC10	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
BC11	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
BC12	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
BC13	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
BC14	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
BC15	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
BC16	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
BC17	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
BC3	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C2	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C23	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C26	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C27	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C3	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C5	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C56	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C58	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C8	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C17	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
BC4	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
BC5	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
BC6	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
BC7	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
BC8	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C14	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C13	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C10	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
BC9	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	

Location no.	Code no.	Description & Specification	Remarks
MC12	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,-,1608	
MC14	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,-,1608	
MC24	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,-,1608	
RC45	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,-,1608	
DC5	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,-,1608	
C9	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,-,1608	
DC21	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,-,1608	
DC3	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,-,1608	
DC4	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,-,1608	
MC35	2203-005221	C-CER,CHIP;15nF,10%,50V,X7R,TP,1608,-	
MC32	2203-005221	C-CER,CHIP;15nF,10%,50V,X7R,TP,1608,-	
PC7	2402-000009	C-AL,SMD;47uF,20%,6.3V,GP,TP,5.3x5.3x5.	
PC5	2402-000009	C-AL,SMD;47uF,20%,6.3V,GP,TP,5.3x5.3x5.	
PC3	2402-000009	C-AL,SMD;47uF,20%,6.3V,GP,TP,5.3x5.3x5.	
C4	2402-000009	C-AL,SMD;47uF,20%,6.3V,GP,TP,5.3x5.3x5.	
C38	2402-000009	C-AL,SMD;47uF,20%,6.3V,GP,TP,5.3x5.3x5.	
PC1	2402-000107	C-AL,SMD;100uF,20%,6.3V,GP,TP,6.6x6.6x5	
RC21	2402-000107	C-AL,SMD;100uF,20%,6.3V,GP,TP,6.6x6.6x5	
RC27	2402-000107	C-AL,SMD;100uF,20%,6.3V,GP,TP,6.6x6.6x5	
C7	2402-000107	C-AL,SMD;100uF,20%,6.3V,GP,TP,6.6x6.6x5	
AC4	2402-000107	C-AL,SMD;100uF,20%,6.3V,GP,TP,6.6x6.6x5	
C1	2402-000107	C-AL,SMD;100uF,20%,6.3V,GP,TP,6.6x6.6x5	
C24	2402-000107	C-AL,SMD;100uF,20%,6.3V,GP,TP,6.6x6.6x5	
DC2	2402-001042	C-AL,SMD;100uF,20%,16V,GP,TP,6.6x6.6x5.	
PC2	2402-001049	C-AL,CHIP;10uF,20%,16V,GP,TP,3.3x3.3x5.4	
PC11	2402-001049	C-AL,CHIP;10uF,20%,16V,GP,TP,3.3x3.3x5.4	
MC10	2402-001049	C-AL,CHIP;10uF,20%,16V,GP,TP,3.3x3.3x5.4	
FREE	2402-001049	C-AL,CHIP;10uF,20%,16V,GP,TP,3.3x3.3x5.4	
PC6	2402-001059	C-AL,SMD;220UF,20%,6.3V,-,TP,6X6.6X6.6	
PC10	2402-001059	C-AL,SMD;220UF,20%,6.3V,-,TP,6X6.6X6.6	
C12	2402-001059	C-AL,SMD;220UF,20%,6.3V,-,TP,6X6.6X6.6	
L16	2703-000125	INDUCTOR-SMD;10uH,10%,2012	
X2	2801-004284	CRYSTAL-SMD;27MHZ,10PPM,28-AAN,20PF,30OH	
AL18	3301-001069	BEAD-SMD;120ohm,1.6x0.8x0.8mm,200mA,TP,	
AL20	3301-001069	BEAD-SMD;120ohm,1.6x0.8x0.8mm,200mA,TP,	
AL22	3301-001069	BEAD-SMD;120ohm,1.6x0.8x0.8mm,200mA,TP,	
AL26	3301-001069	BEAD-SMD;120ohm,1.6x0.8x0.8mm,200mA,TP,	
AL14	3301-001069	BEAD-SMD;120ohm,1.6x0.8x0.8mm,200mA,TP,	
AL15	3301-001069	BEAD-SMD;120ohm,1.6x0.8x0.8mm,200mA,TP,	
AL16	3301-001069	BEAD-SMD;120ohm,1.6x0.8x0.8mm,200mA,TP,	
AL17	3301-001069	BEAD-SMD;120ohm,1.6x0.8x0.8mm,200mA,TP,	
L8	3301-001495	BEAD-SMD;120ohm,2012,2500mA,TP,115ohm/1	
L7	3301-001495	BEAD-SMD;120ohm,2012,2500mA,TP,115ohm/1	
L6	3301-001495	BEAD-SMD;120ohm,2012,2500mA,TP,115ohm/1	
L5	3301-001495	BEAD-SMD;120ohm,2012,2500mA,TP,115ohm/1	
L4	3301-001495	BEAD-SMD;120ohm,2012,2500mA,TP,115ohm/1	
RL1	3301-001495	BEAD-SMD;120ohm,2012,2500mA,TP,115ohm/1	
R1	3301-001495	BEAD-SMD;120ohm,2012,2500mA,TP,115ohm/1	
ML2	3301-001495	BEAD-SMD;120ohm,2012,2500mA,TP,115ohm/1	
ML1	3301-001495	BEAD-SMD;120ohm,2012,2500mA,TP,115ohm/1	
L9	3301-001495	BEAD-SMD;120ohm,2012,2500mA,TP,115ohm/1	
L26	3301-001495	BEAD-SMD;120ohm,2012,2500mA,TP,115ohm/1	
L10	3301-001495	BEAD-SMD;120ohm,2012,2500mA,TP,115ohm/1	
L1	3301-001495	BEAD-SMD;120ohm,2012,2500mA,TP,115ohm/1	
ASL1	3301-001495	BEAD-SMD;120ohm,2012,2500mA,TP,115ohm/1	
AL21	3301-001495	BEAD-SMD;120ohm,2012,2500mA,TP,115ohm/1	
AL19	3301-001495	BEAD-SMD;120ohm,2012,2500mA,TP,115ohm/1	
L2	3301-001495	BEAD-SMD;120ohm,2012,2500mA,TP,115ohm/1	
L19	3301-001495	BEAD-SMD;120ohm,2012,2500mA,TP,115ohm/1	
L17	3301-001495	BEAD-SMD;120ohm,2012,2500mA,TP,115ohm/1	
L13	3301-001495	BEAD-SMD;120ohm,2012,2500mA,TP,115ohm/1	
L12	3301-001495	BEAD-SMD;120ohm,2012,2500mA,TP,115ohm/1	
ACN2	3708-001805	CONNECTOR-FPC/FFC/PIC;20P,1MM,SMD-A,SN,N	
ACN3	3708-001805	CONNECTOR-FPC/FFC/PIC;20P,1MM,SMD-A,SN,N	
CN1	3708-001807	CONNECTOR-FPC/FFC/PIC;11P,1MM,SMD-A,SN,N	
DCN1	3708-001808	CONNECTOR-FPC/FFC/PIC;24P,0.5MM,SMD-A,SN	
CN2	3711-002533	CONNECTOR-HEADER;BOX,5P,1R,2MM,SMD-A,SN,	
CN3	3711-005306	CONNECTOR-HEADER;BOX,4P,1R,2MM,SMD-A,TIN	
PCN1	3711-005307	CONNECTOR-HEADER;BOX,8P,1R,2MM,SMD-S,TIN	
	AH92-02075A	**ASSY PCB;HT-DS700,MAIN PCB ASSY**	
OPT1	0603-001126	OPTIC TRANSMITTER;5V,13.2MB/S,5M,-14.5DB	
ACW7	3708-001094	CONNECTOR-FPC/FFC/PIC;13P,1.25MM,STRAIGH	
ACW4	3708-001122	CONNECTOR-FPC/FFC/PIC;26P,1.25MM,STRAIGH	
ACW11	3708-001760	CONNECTOR-FPC/FFC/PIC;20P,1MM,STRAIGHT,S	
OCW1	3708-001760	CONNECTOR-FPC/FFC/PIC;20P,1MM,STRAIGHT,S	
SCW1	3711-003409	CONNECTOR-HEADER;BOX,3P,1R,2mm,STRAIGHT,	
ACW9	3711-003411	CONNECTOR-HEADER;BOX,5P,1R,2mm,STRAIGHT,	
ACW3	3711-004109	CONNECTOR-HEADER;3WALL,14P,1R,2MM,STRAIG	
ACW2	3711-004109	CONNECTOR-HEADER;3WALL,14P,1R,2MM,STRAIG	
ACW1	3711-004109	CONNECTOR-HEADER;3WALL,14P,1R,2MM,STRAIG	
AJ4	3722-001606	JACK-PIN;4P,3.5mm,NI,BLK(WHT2/RED2),-	
SJACK1	3722-001682	JACK-SCART;21P,-,SN,BLK,-	
SW1	AH34-00015B	SWITCH SLIDE;FKA-22H14,SLIDE,-,-,50V,0.3	
SJACK2	AH37-00005A	JACK---RCA;1P,S-440B,YELLOW,-,SHIELD PLAT	
ACW8	AH39-00614A	WIRE HARNESS;HT-DS400,-,-,7P,-,-,26AWG,-	
	AH63-00386A	SHIELD-SCART;HT-DL100,SPTE 0.3T,-,-,-,-,	
OD10	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
SQ2	0501-000303	TR-SMALL SIGNAL;KSA733,PNP,250mW,TO-92,T	
SQ1	0501-000303	TR-SMALL SIGNAL;KSA733,PNP,250mW,TO-92,T	
SQ7R	0501-000341	TR-SMALL SIGNAL;KSC1623-L,NPN,200mW,SOT-	
SQ7L	0501-000341	TR-SMALL SIGNAL;KSC1623-L,NPN,200mW,SOT-	
SQ3	0501-000637	TR-SMALL SIGNAL;2SC1740S,NPN,300mW,SPT,T	

Location no.	Code no.	Description & Specification	Remarks
AQ8L	0501-002184	TR-SMALL SIGNAL;KTD1304,NPN,200mW,SOT-23	
AQ8R	0501-002184	TR-SMALL SIGNAL;KTD1304,NPN,200mW,SOT-23	
OQ10	0504-000118	TR-DIGITAL;KSR1003,NPN,300MW,22K/22K,TO-	
SQ4	0504-000128	TR-DIGITAL;-,NPN,200MW,22K/22K,SOT-23,TP	
SQ5	0504-000128	TR-DIGITAL;-,NPN,200MW,22K/22K,SOT-23,TP	
SQ6	0504-000156	TR-DIGITAL;KSR2103,PNP,200MW,22K/22K,SOT	
AQ9	0504-000156	TR-DIGITAL;KSR2103,PNP,200MW,22K/22K,SOT	
AIC1	1002-001392	IC-A/D CONVERTER;WM8775EDS,24BIT,SSOP,28	
AR15	2001-000003	R-CARBON;330ohm,5%,1/8W,AA,TP,1.8x3.2mm	
AR17R	2001-000008	R-CARBON;15KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
AR17L	2001-000008	R-CARBON;15KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
AR92	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
AR91	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
AR90	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
OR11	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
AR3R	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
SR7	2001-000302	R-CARBON;10OHM,5%,1/8W,AA,TP,1.8X3.2MM	
AR79	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
AR80	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
SR17	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
AR78	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
AR77	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
AR76	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
SR4	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
SR6	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
SR5	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
SR3	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
SR16	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
AR70	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
AR72	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
AR73	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
AR74	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
AR10	2001-000995	R-CARBON;820OHM,5%,1/8W,AA,TP,1.8X3.2MM	
JW178	2007-000029	R-CHIP;0ohm,5%,1/8W,TP,2012	
JW177	2007-000029	R-CHIP;0ohm,5%,1/8W,TP,2012	
JW171	2007-000029	R-CHIP;0ohm,5%,1/8W,TP,2012	
JW147	2007-000029	R-CHIP;0ohm,5%,1/8W,TP,2012	
JW146	2007-000029	R-CHIP;0ohm,5%,1/8W,TP,2012	
SR13	2007-000030	R-CHIP;560ohm,5%,1/8W,TP,2012	
SR14	2007-000282	R-CHIP;100Kohm,5%,1/8W,TP,2012	
AR47R	2007-000282	R-CHIP;100Kohm,5%,1/8W,TP,2012	
AR47L	2007-000282	R-CHIP;100Kohm,5%,1/8W,TP,2012	
AR45	2007-000290	R-CHIP;100ohm,5%,1/8W,TP,2012	
AR44	2007-000290	R-CHIP;100ohm,5%,1/8W,TP,2012	
AR43	2007-000290	R-CHIP;100ohm,5%,1/8W,TP,2012	
AR42	2007-000290	R-CHIP;100ohm,5%,1/8W,TP,2012	
R40	2007-000300	R-CHIP;10Kohm,5%,1/8W,TP,2012	
SR1	2007-000300	R-CHIP;10Kohm,5%,1/8W,TP,2012	
SR2	2007-000300	R-CHIP;10Kohm,5%,1/8W,TP,2012	
AR1L	2007-000300	R-CHIP;10Kohm,5%,1/8W,TP,2012	
AR1R	2007-000300	R-CHIP;10Kohm,5%,1/8W,TP,2012	
AR3L	2007-000300	R-CHIP;10Kohm,5%,1/8W,TP,2012	
SR18L	2007-000468	R-CHIP;1Kohm,5%,1/8W,TP,2012	
SR18R	2007-000468	R-CHIP;1Kohm,5%,1/8W,TP,2012	
AR14R	2007-000572	R-CHIP;220ohm,5%,1/8W,TP,2012	
AR14L	2007-000572	R-CHIP;220ohm,5%,1/8W,TP,2012	
SR12	2007-000686	R-CHIP;3.3Kohm,5%,1/8W,TP,2012	
AR7R	2007-000710	R-CHIP;3.9Kohm,5%,1/8W,TP,2012	
AR7L	2007-000710	R-CHIP;3.9Kohm,5%,1/8W,TP,2012	
AR4R	2007-000774	R-CHIP;33Kohm,5%,1/8W,TP,2012	
AR4L	2007-000774	R-CHIP;33Kohm,5%,1/8W,TP,2012	
AR2R	2007-000774	R-CHIP;33Kohm,5%,1/8W,TP,2012	
AR2L	2007-000774	R-CHIP;33Kohm,5%,1/8W,TP,2012	
SR15	2007-000872	R-CHIP;4.7Kohm,5%,1/8W,TP,2012	
AR8R	2007-000981	R-CHIP;5.6Kohm,5%,1/8W,TP,2012	
AR8L	2007-000981	R-CHIP;5.6Kohm,5%,1/8W,TP,2012	
AR23R	2007-000981	R-CHIP;5.6Kohm,5%,1/8W,TP,2012	
AR23L	2007-000981	R-CHIP;5.6Kohm,5%,1/8W,TP,2012	
SR8	2007-001133	R-CHIP;68ohm,5%,1/8W,TP,2012	
SR11	2007-001133	R-CHIP;68ohm,5%,1/8W,TP,2012	
SR9	2007-001166	R-CHIP;75ohm,5%,1/8W,TP,2012	
SR22	2007-001166	R-CHIP;75ohm,5%,1/8W,TP,2012	
SR21	2007-001166	R-CHIP;75ohm,5%,1/8W,TP,2012	
SR20	2007-001166	R-CHIP;75ohm,5%,1/8W,TP,2012	
SR10	2007-001166	R-CHIP;75ohm,5%,1/8W,TP,2012	
AR71	2007-001166	R-CHIP;75ohm,5%,1/8W,TP,2012	
AR11	2007-001201	R-CHIP;820ohm,5%,1/8W,TP,2012	
C101	2202-000780	C-CERAMIC,MLC-AXIAL;100nF,+80-20%,50V,Y5	
C104	2202-000780	C-CERAMIC,MLC-AXIAL;100nF,+80-20%,50V,Y5	
C94	2202-000781	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
C93	2202-000781	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
C90	2202-000781	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
C100	2202-000781	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
OC10	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,-,2012	
SC10	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,-,2012	
SC11	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,-,2012	
SC12	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,-,2012	
SC9	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,-,2012	
OC1	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,-,2012	
AC26	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,-,2012	
AC28	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,-,2012	
AC32	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,-,2012	
AC33	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,-,2012	

Location no.	Code no.	Description & Specification	Remarks
AC36	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,-,2012	
C110	2203-000239	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,2012	
C111	2203-000239	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,2012	
C91	2203-000239	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,2012	
C92	2203-000239	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,2012	
C106	2203-000239	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,2012	
C107	2203-000239	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,2012	
C108	2203-000239	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,2012	
C109	2203-000239	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,2012	
SC2	2203-000260	C-CER,CHIP;10nF,10%,50V,X7R,TP,2012	
SC1	2203-000260	C-CER,CHIP;10nF,10%,50V,X7R,TP,2012	
AC20	2203-000595	C-CER,CHIP;0.22NF,5%,50V,C0G,TP,2012	
AC19	2203-000595	C-CER,CHIP;0.22NF,5%,50V,C0G,TP,2012	
AC18	2203-000595	C-CER,CHIP;0.22NF,5%,50V,C0G,TP,2012	
OC11	2203-000609	C-CER,CHIP;22nF,10%,50V,X7R,TP,2012	
AC3R	2203-000787	C-CER,CHIP;0.33NF,5%,50V,C0G,TP,2012	
SC17L	2203-000787	C-CER,CHIP;0.33NF,5%,50V,C0G,TP,2012	
SC17R	2203-000787	C-CER,CHIP;0.33NF,5%,50V,C0G,TP,2012	
AC3L	2203-000787	C-CER,CHIP;0.33NF,5%,50V,C0G,TP,2012	
AC1R	2203-000787	C-CER,CHIP;0.33NF,5%,50V,C0G,TP,2012	
AC1L	2203-000787	C-CER,CHIP;0.33NF,5%,50V,C0G,TP,2012	
AC38	2401-000303	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
AC25	2401-000419	C-AL;10UF,20%,16V,GP,-,5X11,5	
AC27	2401-000419	C-AL;10UF,20%,16V,GP,-,5X11,5	
AC29	2401-000419	C-AL;10UF,20%,16V,GP,-,5X11,5	
AC31	2401-000419	C-AL;10UF,20%,16V,GP,-,5X11,5	
SC13	2401-000918	C-AL;22uF,20%,16V,GP,-,6.3x7,5	
SC7	2401-001092	C-AL;330uF,20%,10V,GP,-,8x11.5,2.5m	
SC6	2401-001092	C-AL;330uF,20%,10V,GP,-,8x11.5,2.5m	
SC5	2401-001092	C-AL;330uF,20%,10V,GP,-,8x11.5,2.5m	
SC4	2401-001092	C-AL;330uF,20%,10V,GP,-,8x11.5,2.5m	
SC3	2401-001092	C-AL;330uF,20%,10V,GP,-,8x11.5,2.5m	
SC16	2401-001092	C-AL;330uF,20%,10V,GP,-,8x11.5,2.5m	
SC15	2401-001092	C-AL;330uF,20%,10V,GP,-,8x11.5,2.5m	
SC14	2401-001092	C-AL;330uF,20%,10V,GP,-,8x11.5,2.5m	
SC8	2401-001893	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
AC12	2401-001975	C-AL;47uF,20%,16V,GP,TP,5x11mm,5mm	
AC7R	2401-002180	C-AL;2.2uF,20%,50V,GP,TP,5x11mm,5mm	
AC7L	2401-002180	C-AL;2.2uF,20%,50V,GP,TP,5x11mm,5mm	
AC4R	2401-002180	C-AL;2.2uF,20%,50V,GP,TP,5x11mm,5mm	
AC2L	2401-002180	C-AL;2.2uF,20%,50V,GP,TP,5x11mm,5mm	
AC2R	2401-002180	C-AL;2.2uF,20%,50V,GP,TP,5x11mm,5mm	
AC4L	2401-002180	C-AL;2.2uF,20%,50V,GP,TP,5x11mm,5mm	
AJW1L	2701-000114	INDUCTOR-AXIAL;10UH,10%,2534	
AJW1R	2701-000114	INDUCTOR-AXIAL;10UH,10%,2534	
VL2	2701-000116	INDUCTOR-AXIAL;10UH,10%,4298	
SL1	2701-000116	INDUCTOR-AXIAL;10UH,10%,4298	
SL2R	2701-000177	INDUCTOR-AXIAL;33UH,10%,2534	
SL2L	2701-000177	INDUCTOR-AXIAL;33UH,10%,2534	
SBD1	3301-000297	BEAD-AXIAL;25ohm,3.6x1.2x5.7mm,,TP,,,	
ABD6	3301-000297	BEAD-AXIAL;25ohm,3.6x1.2x5.7mm,,TP,,,	
ABD5	3301-000297	BEAD-AXIAL;25ohm,3.6x1.2x5.7mm,,TP,,,	
ABD2	3301-000297	BEAD-AXIAL;25ohm,3.6x1.2x5.7mm,,TP,,,	
HBD1	3301-001495	BEAD-SMD;120ohm,2012,2500mA,TP,115ohm/1	
HBD2	3301-001495	BEAD-SMD;120ohm,2012,2500mA,TP,115ohm/1	
HBD3	3301-001495	BEAD-SMD;120ohm,2012,2500mA,TP,115ohm/1	
OBD1	3301-001495	BEAD-SMD;120ohm,2012,2500mA,TP,115ohm/1	
ABD8	3301-001495	BEAD-SMD;120ohm,2012,2500mA,TP,115ohm/1	
ABD1	3301-001495	BEAD-SMD;120ohm,2012,2500mA,TP,115ohm/1	
ABD3	3301-001495	BEAD-SMD;120ohm,2012,2500mA,TP,115ohm/1	
ABD4	3301-001495	BEAD-SMD;120ohm,2012,2500mA,TP,115ohm/1	
ABD7	3301-001495	BEAD-SMD;120ohm,2012,2500mA,TP,115ohm/1	
	AH92-02076B	**ASSY PCB-FRONT;HT-DS700,CE**	
ULD2	0601-001432	LED;ROUND,BLUE,3mm,455nm	
ULD1	0601-001432	LED;ROUND,BLUE,3mm,455nm	
UEYE	0609-001202	MODULE REMOCON;HORIZONTAL,12.4MM,TR	
E-VR	3406-001047	SWITCH-ROTARY;5V DC,0.5mA,-,12mm	
FCW1	3708-001924	CONNECTOR-FPC/FFC/PIC;20P,1.25MM,STRAIGH	
FCW4	3711-002808	CONNECTOR-HEADER;BOX,7P,1R,2mm,STRAIGHT,	
FCW3	3711-003409	CONNECTOR-HEADER;BOX,3P,1R,2mm,STRAIGHT,	
FCW2	3711-003409	CONNECTOR-HEADER;BOX,3P,1R,2mm,STRAIGHT,	
HJACK	3722-001588	JACK-PHONE;7P,3.6PI,AG,BLK,-	
	3722-001693	JACK-PIN;3P,8.3PI,NI-P,GRN/BLK/RED,-	
VFD	AH07-00131A	VF DISPLAY;HNA-11SM50T,HT-DS400,118.2*20	
FW6	AH39-00427A	WIRE HARNESS;-,-,-,9P,-,-,-,5295,51004,-	
FCW2-1	AH39-00479A	WIRE HARNESS;HT-DB300,-,-,3P,-,-,26AWG,5	
SCW1-1	AH39-00512A	LEAD CONNECTOR-ASSY;-,-,-,5P,-,-,-,5295,	
FCW3-1	AH39-00608A	WIRE HARNESS;HT-DS400,-,-,3P,-,-,26AWG,5	
FW5	AH39-00615A	WIRE HARNESS;HT-DS400,-,-,3P,-,-,28AWG,2	
FCW4-1	AH39-00619A	WIRE HARNESS;HT-DS700,-,-,7P,-,-,26AWG,5	
	AH61-01405A	HOLDER-VFD;HT-DB120,ABS,-,-,-,BLK,-	
FD53	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150MA,SOD-3	
FD52	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150MA,SOD-3	
FD51	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150MA,SOD-3	
FD1	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150MA,SOD-3	
FD2	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150MA,SOD-3	
FD50	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150MA,SOD-3	
FD3	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
FQ4	0504-000156	TR-DIGITAL;KSR2103,PNP,200MW,22K/22K,SOT	
ULD6	0601-001238	LED;ROUND,RED,3.1mm,697nm	
FIC1	1003-001708	IC-VFD;S5G5128A,LQFP,64P,1063MIL,-,-	
FR20	2001-000552	R-CARBON;270OHM,5%,1/4W,AA,TP,2.4X6.4MM	

Location no.	Code no.	Description & Specification	Remarks
JW6	2007-000029	R-CHIP;0ohm,5%,1/8W,TP,2012	
JW7	2007-000029	R-CHIP;0ohm,5%,1/8W,TP,2012	
JW8	2007-000029	R-CHIP;0ohm,5%,1/8W,TP,2012	
JW5	2007-000029	R-CHIP;0ohm,5%,1/8W,TP,2012	
JW3	2007-000029	R-CHIP;0ohm,5%,1/8W,TP,2012	
JW2	2007-000029	R-CHIP;0ohm,5%,1/8W,TP,2012	
JW13	2007-000029	R-CHIP;0ohm,5%,1/8W,TP,2012	
FR2	2007-000241	R-CHIP;1.5Kohm,5%,1/8W,TP,2012	
FR3	2007-000267	R-CHIP;1.8Kohm,5%,1/8W,TP,2012	
HR90	2007-000290	R-CHIP;100ohm,5%,1/8W,TP,2012	
FR21	2007-000300	R-CHIP;10Kohm,5%,1/8W,TP,2012	
FR22	2007-000300	R-CHIP;10Kohm,5%,1/8W,TP,2012	
FR23	2007-000300	R-CHIP;10Kohm,5%,1/8W,TP,2012	
FR24	2007-000300	R-CHIP;10Kohm,5%,1/8W,TP,2012	
FR19	2007-000300	R-CHIP;10Kohm,5%,1/8W,TP,2012	
FR18	2007-000300	R-CHIP;10Kohm,5%,1/8W,TP,2012	
FR16	2007-000300	R-CHIP;10Kohm,5%,1/8W,TP,2012	
FR15	2007-000300	R-CHIP;10Kohm,5%,1/8W,TP,2012	
FR13	2007-000300	R-CHIP;10Kohm,5%,1/8W,TP,2012	
FR17	2007-000449	R-CHIP;180ohm,5%,1/8W,TP,2012	
FR27	2007-000468	R-CHIP;1Kohm,5%,1/8W,TP,2012	
FR26	2007-000468	R-CHIP;1Kohm,5%,1/8W,TP,2012	
FR25	2007-000468	R-CHIP;1Kohm,5%,1/8W,TP,2012	
FR1	2007-000468	R-CHIP;1Kohm,5%,1/8W,TP,2012	
FR4	2007-000493	R-CHIP;2.2Kohm,5%,1/8W,TP,2012	
FR5	2007-000686	R-CHIP;3.3Kohm,5%,1/8W,TP,2012	
FR6	2007-000872	R-CHIP;4.7Kohm,5%,1/8W,TP,2012	
FR14	2007-001009	R-CHIP;51Kohm,5%,1/8W,TP,2012	
FC51	2203-000203	C-CER,CHIP;100nF,10%,16V,X7R,TP,2012,2mm	
FC11	2203-000203	C-CER,CHIP;100nF,10%,16V,X7R,TP,2012,2mm	
FC2	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,-,2012	
FC17	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,-,2012	
FC13	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,-,2012	
FC12	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,-,2012	
FC1	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,-,2012	
FC95	2203-000239	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,2012	
HC1L	2203-000239	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,2012	
HC1R	2203-000239	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,2012	
FC94	2203-000239	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,2012	
FC90	2203-000239	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,2012	
FC91	2203-000239	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,2012	
FC93	2203-000239	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,2012	
MC90	2203-000260	C-CER,CHIP;10nF,10%,50V,X7R,TP,2012	
FC97	2203-000260	C-CER,CHIP;10nF,10%,50V,X7R,TP,2012	
FC92	2203-000260	C-CER,CHIP;10nF,10%,50V,X7R,TP,2012	
FC5	2203-000260	C-CER,CHIP;10nF,10%,50V,X7R,TP,2012	
C52	2203-000260	C-CER,CHIP;10nF,10%,50V,X7R,TP,2012	
HC2R	2203-000533	C-CER,CHIP;2.7nF,10%,50V,X7R,TP,2012,-	
HC2L	2203-000533	C-CER,CHIP;2.7nF,10%,50V,X7R,TP,2012,-	
FC9	2203-000595	C-CER,CHIP;0.22NF,5%,50V,C0G,TP,2012	
FC8	2203-000595	C-CER,CHIP;0.22NF,5%,50V,C0G,TP,2012	
FC50	2203-000595	C-CER,CHIP;0.22NF,5%,50V,C0G,TP,2012	
FC10	2203-000595	C-CER,CHIP;0.22NF,5%,50V,C0G,TP,2012	
HC3R	2203-000818	C-CER,CHIP;0.033NF,5%,50V,C0G,TP,2012	
HC3L	2203-000818	C-CER,CHIP;0.033NF,5%,50V,C0G,TP,2012	
FC7	2203-000979	C-CER,CHIP;47nF,10%,50V,X7R,TP,2012	
FC6	2203-000979	C-CER,CHIP;47nF,10%,50V,X7R,TP,2012	
FC4	2203-000979	C-CER,CHIP;47nF,10%,50V,X7R,TP,2012	
FC3	2401-000243	C-AL;100uF,20%,10V,GP,TP,6.3x5,5	
FC16	2401-000485	C-AL;10UF,20%,50V,GP,TP,6.3X5MM,2.5	
FC15	2401-000485	C-AL;10UF,20%,50V,GP,TP,6.3X5MM,2.5	
FC14	2401-000485	C-AL;10UF,20%,50V,GP,TP,6.3X5MM,2.5	
HL1R	3301-000297	BEAD-AXIAL;25ohm,3.6x1.2x5.7mm,,TP,,,	
HL1L	3301-000297	BEAD-AXIAL;25ohm,3.6x1.2x5.7mm,,TP,,,	
FBD1	3301-001495	BEAD-SMD;120ohm,2012,2500mA,TP,115ohm/1	
SW4	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
SW5	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
SW6	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
SW3	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
SW1	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
SW10	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
SW2	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
	AH92-02077A	**ASSY PCB;HT-DS700,MICOM PCB ASSY**	
UD7	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
UD6	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
UD3	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
UR9	2001-000552	R-CARBON;270OHM,5%,1/4W,AA,TP,2.4X6.4MM	
UX1	2802-001174	RESONATOR-CERAMIC;10MHZ,0.5%,BK,8X3.5X3M	
UCW6	3708-000303	CONNECTOR-FPC/FFC/PIC;6P,1.25MM,STRAIGHT	
UCW1	3708-001661	CONNECTOR-FPC/FFC/PIC;20P,1.25MM,ANGLE,S	
UCW4	3710-001421	CONNECTOR-SOCKET;14P,1R,2mm,ANGLE,SN	
UCW3	3710-001421	CONNECTOR-SOCKET;14P,1R,2mm,ANGLE,SN	
UCW2	3710-001421	CONNECTOR-SOCKET;14P,1R,2mm,ANGLE,SN	
UCW9	3711-003411	CONNECTOR-HEADER;BOX,5P,1R,2mm,STRAIGHT,	
UJ2	3722-000351	JACK-PHONE;11P,3.5PI,AG,BLK,-	
UJ1	3722-000351	JACK-PHONE;11P,3.5PI,AG,BLK,-	
UCW8	AH39-00512A	LEAD CONNECTOR-ASSY;-,-,-,5P,-,-,-,5295,	
	AH61-01140A	BRACKET-PCB;HT-DM150,SPTE 0.5T,-,-,-,-,-	
XD23	0401-001110	DIODE-SWITCHING;-,80V,100MA,SOD-523,TP	
XD4	0401-001110	DIODE-SWITCHING;-,80V,100MA,SOD-523,TP	
XD5	0401-001110	DIODE-SWITCHING;-,80V,100MA,SOD-523,TP	
XD7	0401-001110	DIODE-SWITCHING;-,80V,100MA,SOD-523,TP	

Location no.	Code no.	Description & Specification	Remarks
XD8	0401-001110	DIODE-SWITCHING;-,80V,100MA,SOD-523,TP	
XD17	0401-001110	DIODE-SWITCHING;-,80V,100MA,SOD-523,TP	
UD10	0401-001110	DIODE-SWITCHING;-,80V,100MA,SOD-523,TP	
UD4	0401-001110	DIODE-SWITCHING;-,80V,100MA,SOD-523,TP	
UD5	0401-001110	DIODE-SWITCHING;-,80V,100MA,SOD-523,TP	
UD8	0401-001110	DIODE-SWITCHING;-,80V,100MA,SOD-523,TP	
UD9	0401-001110	DIODE-SWITCHING;-,80V,100MA,SOD-523,TP	
UQ3	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
UQ2	0504-000128	TR-DIGITAL;-,NPN,200MW,22K/22K,SOT-23,TP	
UQ1	0504-000128	TR-DIGITAL;-,NPN,200MW,22K/22K,SOT-23,TP	
UIC3	1003-000262	IC-LINE TRANSCEIVER;MAX232CSE,SOP,16P,15	
UR69	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
UR68	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
UR67	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
UR70	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
UR71	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
UR72	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
UR61	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
UR62	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
UR63	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
UR64	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
UR65	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
UR66	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
UR79	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
UR80	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
UR81	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
UR82	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
UR83	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
UR84	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
UR73	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
UR74	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
UR75	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
UR76	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
UR77	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
UR78	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
UR60	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
UR42	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
UR43	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
UR44	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
UR45	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
UR46	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
UR47	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
UR150	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
UR151	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
UR160	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
UR170	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
UR171	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
UR41	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
UR54	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
UR55	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
UR56	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
UR57	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
UR58	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
UR59	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
UR48	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
UR49	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
UR50	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
UR51	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
UR52	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
UR53	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
UR4	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
UR8	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
UR96	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
UR97	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
UR2	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
UR27	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
UR29	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
UR30	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
UR40	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
UR5	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
UR6	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
UR26	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
UR11	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
UR20	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
UR21	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
UR23	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
UR24	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
UR25	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
UR100	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
UR93	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	
UR92	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	
UR91	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	
UR90	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	
UR3	2007-000106	R-CHIP;220Kohm,5%,1/10W,TP,1608	
UR18	2007-000109	R-CHIP;1Mohm,5%,1/10W,TP,1608	
UR1	2007-000124	R-CHIP;2.2Kohm,5%,1/10W,TP,1608	
UR7	2007-000402	R-CHIP;150ohm,5%,1/10W,TP,1608	
UC8	2203-000062	C-CER,CHIP;47nF,+80-20%,50V,Y5V,TP,1608	
UC7	2203-000062	C-CER,CHIP;47nF,+80-20%,50V,Y5V,TP,1608	
UC60	2203-000062	C-CER,CHIP;47nF,+80-20%,50V,Y5V,TP,1608	
UC4	2203-000062	C-CER,CHIP;47nF,+80-20%,50V,Y5V,TP,1608	
UC10	2203-000062	C-CER,CHIP;47nF,+80-20%,50V,Y5V,TP,1608	
UC9	2203-000260	C-CER,CHIP;10nF,10%,50V,X7R,TP,2012	

Location no.	Code no.	Description & Specification	Remarks
UC76	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608,-	
UC75	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608,-	
UC74	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608,-	
UC73	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608,-	
UC72	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608,-	
UC71	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608,-	
UC70	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608,-	
UC6	2401-000243	C-AL;100uF,20%,10V,GP,TP,6.3x5,5	
UC14	2401-000243	C-AL;100uF,20%,10V,GP,TP,6.3x5,5	
UC1	2401-000243	C-AL;100uF,20%,10V,GP,TP,6.3x5,5	
UC54	2401-000588	C-AL;1uF,20%,50V,GP,TP,3x5,2.5	
UC53	2401-000588	C-AL;1uF,20%,50V,GP,TP,3x5,2.5	
UC52	2401-000588	C-AL;1uF,20%,50V,GP,TP,3x5,2.5	
UC51	2401-000588	C-AL;1uF,20%,50V,GP,TP,3x5,2.5	
UC50	2401-000588	C-AL;1uF,20%,50V,GP,TP,3x5,2.5	
UC3	2401-000759	C-AL;220nF,20%,50V,GP,TP,5x11mm,5mm	
UC2	2401-003336	C-AL;4.7UF,20%,50V,GP,TP,5X5,2	
UC5	2409-000123	C-EDL;47000uF,4uA,5.5V,-,BK,-,5mm	
UB1	3301-001069	BEAD-SMD;120ohm,1.6x0.8x0.8mm,200mA,TP,	
FB8	3301-001069	BEAD-SMD;120ohm,1.6x0.8x0.8mm,200mA,TP,	
FB7	3301-001069	BEAD-SMD;120ohm,1.6x0.8x0.8mm,200mA,TP,	
FB6	3301-001069	BEAD-SMD;120ohm,1.6x0.8x0.8mm,200mA,TP,	
FB5	3301-001069	BEAD-SMD;120ohm,1.6x0.8x0.8mm,200mA,TP,	
UIC1	AH11-00140A	MASK ROM;LC877448A-53Y4,HT-DS400,48K,-,	
	AH92-02078A	**ASSY PCB;HT-DS700,AMP PCB ASSY**	
FR1	2003-000777	R-METAL OXIDE(S);68ohm,5%,2W,AA,TP,4x12m	
C20	2401-000118	C-AL;1000uF,20%,10V,GP,TP,10x12.5,5	
C8RL	2401-003564	C-AL;1000uF,20%,35V,LZ,TP,12.5X25mm	
C8RR	2401-003564	C-AL;1000uF,20%,35V,LZ,TP,12.5X25mm	
C8S	2401-003564	C-AL;1000uF,20%,35V,LZ,TP,12.5X25mm	
C8C	2401-003564	C-AL;1000uF,20%,35V,LZ,TP,12.5X25mm	
C8FL	2401-003564	C-AL;1000uF,20%,35V,LZ,TP,12.5X25mm	
C8FR	2401-003564	C-AL;1000uF,20%,35V,LZ,TP,12.5X25mm	
OSC1	2804-001604	OSCILLATOR-CLOCK;12.288MHZ,50PPM,10 TTL,	
J1	3708-001122	CONNECTOR-FPC/FFC/PIC;26P,1.25MM,STRAIGH	
FJ1	3711-000820	CONNECTOR-HEADER;BOX,2P,1R,2.5MM,STRAIGH	
SPK1	3716-001218	TERMINAL-BLOCK;-,12,4.8mm,40V,5A	
L2C	AH27-00055A	COIL CHOKE;DBF-1310A,HT-DS600,10uH,-,-,2	
L2FL	AH27-00055A	COIL CHOKE;DBF-1310A,HT-DS600,10uH,-,-,2	
L2FR	AH27-00055A	COIL CHOKE;DBF-1310A,HT-DS600,10uH,-,-,2	
L2RL	AH27-00055A	COIL CHOKE;DBF-1310A,HT-DS600,10uH,-,-,2	
L2RR	AH27-00055A	COIL CHOKE;DBF-1310A,HT-DS600,10uH,-,-,2	
L2S	AH27-00055A	COIL CHOKE;DBF-1310A,HT-DS600,10uH,-,-,2	
L1C	AH27-00055A	COIL CHOKE;DBF-1310A,HT-DS600,10uH,-,-,2	
L1FL	AH27-00055A	COIL CHOKE;DBF-1310A,HT-DS600,10uH,-,-,2	
L1FR	AH27-00055A	COIL CHOKE;DBF-1310A,HT-DS600,10uH,-,-,2	
L1RL	AH27-00055A	COIL CHOKE;DBF-1310A,HT-DS600,10uH,-,-,2	
L1RR	AH27-00055A	COIL CHOKE;DBF-1310A,HT-DS600,10uH,-,-,2	
L1S	AH27-00055A	COIL CHOKE;DBF-1310A,HT-DS600,10uH,-,-,2	
J2	AH39-00018B	LEAD CONNECTOR ASSY;MAX-B420,-,-,6P,-,-,	
D3	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150MA,SOD-3	
D4	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150MA,SOD-3	
D2	0402-000309	DIODE-RECTIFIER;1SR154-400,400V,1A,SOD-1	
D1	0402-000309	DIODE-RECTIFIER;1SR154-400,400V,1A,SOD-1	
ZD3	0403-001064	DIODE-ZENER;RLZ5.1B,4.94-5.2V,500MW,LL-3	
Q2	0501-000303	TR-SMALL SIGNAL;KSA733,PNP,250mW,TO-92,T	
HIC	1201-000163	IC-OP AMP;4560,SOP,8P,173MIL,DUAL,100V/m	
SIC	1201-000163	IC-OP AMP;4560,SOP,8P,173MIL,DUAL,100V/m	
IC1RL	1201-002115	IC-AUDIO AMP;TAS5121,PSOP3,36P,15.9X11MM	
IC1RR	1201-002115	IC-AUDIO AMP;TAS5121,PSOP3,36P,15.9X11MM	
IC1S	1201-002115	IC-AUDIO AMP;TAS5121,PSOP3,36P,15.9X11MM	
IC1FR	1201-002115	IC-AUDIO AMP;TAS5121,PSOP3,36P,15.9X11MM	
IC1FL	1201-002115	IC-AUDIO AMP;TAS5121,PSOP3,36P,15.9X11MM	
IC1C	1201-002115	IC-AUDIO AMP;TAS5121,PSOP3,36P,15.9X11MM	
IC3	1202-001061	IC-VOLTAGE COMP;;LMV331M5,SOT-23,5P,3X1.	
U1	1204-002226	IC-MODULATOR;PS9818,QFP,100P,14X14MM,PLA	
R8	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608	
R9	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608	
SR10L	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608	
SR10R	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608	
SR1L	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608	
R7	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608	
R23	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608	
R47	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608	
R48	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608	
R5	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608	
R6	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608	
SR5R	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608	
SR6L	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608	
SR6R	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608	
SR9L	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608	
SR9R	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608	
SR5L	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608	
SR1R	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608	
SR3L	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608	
SR3L	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608	
SR3R	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608	
SR3R	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608	
R22	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608	
HR5R	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608	
HR6L	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608	
HR6R	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608	

Location no.	Code no.	Description & Specification	Remarks
HR9L	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608	
R10C	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608	
HR5L	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608	
HR10R	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608	
HR1L	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608	
HR1R	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608	
HR3L	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608	
HR3R	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608	
R12FL	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608	
R12FR	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608	
R12RL	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608	
R12RR	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608	
R12S	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608	
R12C	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608	
R10FL	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608	
R10FR	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608	
R10RL	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608	
R10RR	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608	
R10S	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608	
R1RL	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
R1RR	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
R1S	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
R1C	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
R1FL	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
R1FR	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
R31	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	
R30	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	
R29	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	
R28	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	
R32	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	
R33	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	
R34	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	
R35	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	
R27	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	
R11	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	
R12	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	
R13	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	
R14	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	
R26	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	
R15	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	
R149	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	
R148	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	
R3	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
R2S	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
R2RR	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
R4	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
SR1	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
SR2	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
R1	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
R2	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
R2C	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
R2FL	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
R2FR	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
R2RL	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
R10	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R41	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R43	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R48	2007-000094	R-CHIP;22Kohm,5%,1/10W,TP,1608	
SR2L	2007-000094	R-CHIP;22Kohm,5%,1/10W,TP,1608	
SR2R	2007-000094	R-CHIP;22Kohm,5%,1/10W,TP,1608	
SR4L	2007-000094	R-CHIP;22Kohm,5%,1/10W,TP,1608	
SR4R	2007-000094	R-CHIP;22Kohm,5%,1/10W,TP,1608	
HR2L	2007-000094	R-CHIP;22Kohm,5%,1/10W,TP,1608	
HR2R	2007-000094	R-CHIP;22Kohm,5%,1/10W,TP,1608	
HR4L	2007-000094	R-CHIP;22Kohm,5%,1/10W,TP,1608	
HR4R	2007-000094	R-CHIP;22Kohm,5%,1/10W,TP,1608	
R42	2007-000094	R-CHIP;22Kohm,5%,1/10W,TP,1608	
SR7L	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
SR7R	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
SR8L	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
SR8R	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
R40	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
HR7L	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
HR7R	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
HR8L	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
HR8R	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
SR9R	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	
SR10L	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	
R17	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	
HR9R	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	
HR10L	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	
R7C	2007-000253	R-CHIP;1.5ohm,5%,1/4W,TP,3216	
R6S	2007-000253	R-CHIP;1.5ohm,5%,1/4W,TP,3216	
R6RR	2007-000253	R-CHIP;1.5ohm,5%,1/4W,TP,3216	
R6RL	2007-000253	R-CHIP;1.5ohm,5%,1/4W,TP,3216	
R7FL	2007-000253	R-CHIP;1.5ohm,5%,1/4W,TP,3216	
R7FR	2007-000253	R-CHIP;1.5ohm,5%,1/4W,TP,3216	
R7RL	2007-000253	R-CHIP;1.5ohm,5%,1/4W,TP,3216	
R7RR	2007-000253	R-CHIP;1.5ohm,5%,1/4W,TP,3216	
R7S	2007-000253	R-CHIP;1.5ohm,5%,1/4W,TP,3216	
R6FR	2007-000253	R-CHIP;1.5ohm,5%,1/4W,TP,3216	
R125	2007-000253	R-CHIP;1.5ohm,5%,1/4W,TP,3216	
R126	2007-000253	R-CHIP;1.5ohm,5%,1/4W,TP,3216	

Location no.	Code no.	Description & Specification	Remarks
R127	2007-000253	R-CHIP;1.5ohm,5%,1/4W,TP,3216	
R128	2007-000253	R-CHIP;1.5ohm,5%,1/4W,TP,3216	
R129	2007-000253	R-CHIP;1.5ohm,5%,1/4W,TP,3216	
R6FL	2007-000253	R-CHIP;1.5ohm,5%,1/4W,TP,3216	
R6C	2007-000253	R-CHIP;1.5ohm,5%,1/4W,TP,3216	
R46	2007-000253	R-CHIP;1.5ohm,5%,1/4W,TP,3216	
R130	2007-000253	R-CHIP;1.5ohm,5%,1/4W,TP,3216	
R21	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	
R20	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	
HR2	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	
HR1	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	
R9FR	2007-000462	R-CHIP;18ohm,5%,1/8W,TP,2012	
R9FL	2007-000462	R-CHIP;18ohm,5%,1/8W,TP,2012	
R9C	2007-000462	R-CHIP;18ohm,5%,1/8W,TP,2012	
R9RL	2007-000462	R-CHIP;18ohm,5%,1/8W,TP,2012	
R9RR	2007-000462	R-CHIP;18ohm,5%,1/8W,TP,2012	
R9S	2007-000462	R-CHIP;18ohm,5%,1/8W,TP,2012	
R8C	2007-000462	R-CHIP;18ohm,5%,1/8W,TP,2012	
R8FL	2007-000462	R-CHIP;18ohm,5%,1/8W,TP,2012	
R8FR	2007-000462	R-CHIP;18ohm,5%,1/8W,TP,2012	
R8S	2007-000462	R-CHIP;18ohm,5%,1/8W,TP,2012	
R8RR	2007-000462	R-CHIP;18ohm,5%,1/8W,TP,2012	
R8RL	2007-000462	R-CHIP;18ohm,5%,1/8W,TP,2012	
R5S	2007-000693	R-CHIP;3.3ohm,1%,1/10W,TP,1608	
R5RR	2007-000693	R-CHIP;3.3ohm,1%,1/10W,TP,1608	
R5RL	2007-000693	R-CHIP;3.3ohm,1%,1/10W,TP,1608	
R5FR	2007-000693	R-CHIP;3.3ohm,1%,1/10W,TP,1608	
R5FL	2007-000693	R-CHIP;3.3ohm,1%,1/10W,TP,1608	
R5C	2007-000693	R-CHIP;3.3ohm,1%,1/10W,TP,1608	
R150	2007-000941	R-CHIP;47Kohm,5%,1/8W,TP,2012	
R4C	2007-001806	R-CHIP;1.5ohm,5%,1/10W,BK,1608	
R4FL	2007-001806	R-CHIP;1.5ohm,5%,1/10W,BK,1608	
R4FR	2007-001806	R-CHIP;1.5ohm,5%,1/10W,BK,1608	
R4RL	2007-001806	R-CHIP;1.5ohm,5%,1/10W,BK,1608	
R4RR	2007-001806	R-CHIP;1.5ohm,5%,1/10W,BK,1608	
R4S	2007-001806	R-CHIP;1.5ohm,5%,1/10W,BK,1608	
R3C	2007-001806	R-CHIP;1.5ohm,5%,1/10W,BK,1608	
R3FL	2007-001806	R-CHIP;1.5ohm,5%,1/10W,BK,1608	
R3FR	2007-001806	R-CHIP;1.5ohm,5%,1/10W,BK,1608	
R3S	2007-001806	R-CHIP;1.5ohm,5%,1/10W,BK,1608	
R3RR	2007-001806	R-CHIP;1.5ohm,5%,1/10W,BK,1608	
R3RL	2007-001806	R-CHIP;1.5ohm,5%,1/10W,BK,1608	
R13C	2007-002425	R-CHIP;1ohm,5%,1/10W,TP,1608	
R13FL	2007-002425	R-CHIP;1ohm,5%,1/10W,TP,1608	
R13FR	2007-002425	R-CHIP;1ohm,5%,1/10W,TP,1608	
R13RL	2007-002425	R-CHIP;1ohm,5%,1/10W,TP,1608	
R13RR	2007-002425	R-CHIP;1ohm,5%,1/10W,TP,1608	
R13S	2007-002425	R-CHIP;1ohm,5%,1/10W,TP,1608	
R124	2007-002425	R-CHIP;1ohm,5%,1/10W,TP,1608	
R11C	2007-002425	R-CHIP;1ohm,5%,1/10W,TP,1608	
R11FL	2007-002425	R-CHIP;1ohm,5%,1/10W,TP,1608	
R11FR	2007-002425	R-CHIP;1ohm,5%,1/10W,TP,1608	
R11RL	2007-002425	R-CHIP;1ohm,5%,1/10W,TP,1608	
R11RR	2007-002425	R-CHIP;1ohm,5%,1/10W,TP,1608	
R11S	2007-002425	R-CHIP;1ohm,5%,1/10W,TP,1608	
CJ2	2007-007625	R-CHIP;0OHM,5%,1W,DA,TP,6432	
CJ1	2007-007625	R-CHIP;0OHM,5%,1W,DA,TP,6432	
C6	2203-000062	C-CER,CHIP;47nF,+80-20%,50V,Y5V,TP,1608	
SC1R	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
SC1L	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
HC9R	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
HC9L	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
HC3R	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
SC2L	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
SR1R	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
SR1L	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
SC9R	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
SC9L	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
SC2R	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
C1RR	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
C1RL	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
C1FR	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
C1FL	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
C1C	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
C1S	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
HC3L	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
HC2R	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
HC2L	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
HC1R	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
HC1L	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
C6C	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C16S	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C16RR	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C16RL	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C6FL	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C6FR	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C6RL	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C6RR	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C6S	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C16FR	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C12C	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C12FL	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C12FR	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	

Location no.	Code no.	Description & Specification	Remarks
C12RL	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C12RR	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C16FL	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C16C	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C142	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C12S	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C7	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,TP,1608,-	
C14C	2203-000787	C-CER,CHIP;0.33NF,5%,50V,C0G,TP,2012	
C14FL	2203-000787	C-CER,CHIP;0.33NF,5%,50V,C0G,TP,2012	
C14FR	2203-000787	C-CER,CHIP;0.33NF,5%,50V,C0G,TP,2012	
C14RL	2203-000787	C-CER,CHIP;0.33NF,5%,50V,C0G,TP,2012	
C14RR	2203-000787	C-CER,CHIP;0.33NF,5%,50V,C0G,TP,2012	
C14S	2203-000787	C-CER,CHIP;0.33NF,5%,50V,C0G,TP,2012	
C13C	2203-000787	C-CER,CHIP;0.33NF,5%,50V,C0G,TP,2012	
C13FL	2203-000787	C-CER,CHIP;0.33NF,5%,50V,C0G,TP,2012	
C13FR	2203-000787	C-CER,CHIP;0.33NF,5%,50V,C0G,TP,2012	
C13S	2203-000787	C-CER,CHIP;0.33NF,5%,50V,C0G,TP,2012	
C13RR	2203-000787	C-CER,CHIP;0.33NF,5%,50V,C0G,TP,2012	
C13RL	2203-000787	C-CER,CHIP;0.33NF,5%,50V,C0G,TP,2012	
SC6L	2203-000998	C-CER,CHIP;0.047NF,5%,50V,C0G,TP,1608	
SC6R	2203-000998	C-CER,CHIP;0.047NF,5%,50V,C0G,TP,1608	
SC7L	2203-000998	C-CER,CHIP;0.047NF,5%,50V,C0G,TP,1608	
SC7R	2203-000998	C-CER,CHIP;0.047NF,5%,50V,C0G,TP,1608	
HC6L	2203-000998	C-CER,CHIP;0.047NF,5%,50V,C0G,TP,1608	
HC6R	2203-000998	C-CER,CHIP;0.047NF,5%,50V,C0G,TP,1608	
HC7L	2203-000998	C-CER,CHIP;0.047NF,5%,50V,C0G,TP,1608	
HC7R	2203-000998	C-CER,CHIP;0.047NF,5%,50V,C0G,TP,1608	
C5FR	2203-002398	C-CER,CHIP;22nF,10%,50V,X7R,TP,1608	
C5FL	2203-002398	C-CER,CHIP;22nF,10%,50V,X7R,TP,1608	
C5C	2203-002398	C-CER,CHIP;22nF,10%,50V,X7R,TP,1608	
C5RL	2203-002398	C-CER,CHIP;22nF,10%,50V,X7R,TP,1608	
C5RR	2203-002398	C-CER,CHIP;22nF,10%,50V,X7R,TP,1608	
C5S	2203-002398	C-CER,CHIP;22nF,10%,50V,X7R,TP,1608	
C18C	2203-002398	C-CER,CHIP;22nF,10%,50V,X7R,TP,1608	
C18FL	2203-002398	C-CER,CHIP;22nF,10%,50V,X7R,TP,1608	
C18FR	2203-002398	C-CER,CHIP;22nF,10%,50V,X7R,TP,1608	
C18S	2203-002398	C-CER,CHIP;22nF,10%,50V,X7R,TP,1608	
C18RR	2203-002398	C-CER,CHIP;22nF,10%,50V,X7R,TP,1608	
C18RL	2203-002398	C-CER,CHIP;22nF,10%,50V,X7R,TP,1608	
C2S	2203-005171	C-CER,CHIP;1000nF,10%,16V,X7R,-,2012	
C2RR	2203-005171	C-CER,CHIP;1000nF,10%,16V,X7R,-,2012	
C2RL	2203-005171	C-CER,CHIP;1000nF,10%,16V,X7R,-,2012	
C2FR	2203-005171	C-CER,CHIP;1000nF,10%,16V,X7R,-,2012	
C2FL	2203-005171	C-CER,CHIP;1000nF,10%,16V,X7R,-,2012	
C2C	2203-005171	C-CER,CHIP;1000nF,10%,16V,X7R,-,2012	
C3S	2203-005171	C-CER,CHIP;1000nF,10%,16V,X7R,-,2012	
C3RR	2203-005171	C-CER,CHIP;1000nF,10%,16V,X7R,-,2012	
C3RL	2203-005171	C-CER,CHIP;1000nF,10%,16V,X7R,-,2012	
C3FR	2203-005171	C-CER,CHIP;1000nF,10%,16V,X7R,-,2012	
C3FL	2203-005171	C-CER,CHIP;1000nF,10%,16V,X7R,-,2012	
C3C	2203-005171	C-CER,CHIP;1000nF,10%,16V,X7R,-,2012	
C19S	2203-005171	C-CER,CHIP;1000nF,10%,16V,X7R,-,2012	
C19RR	2203-005171	C-CER,CHIP;1000nF,10%,16V,X7R,-,2012	
C19RL	2203-005171	C-CER,CHIP;1000nF,10%,16V,X7R,-,2012	
C19FR	2203-005171	C-CER,CHIP;1000nF,10%,16V,X7R,-,2012	
C19FL	2203-005171	C-CER,CHIP;1000nF,10%,16V,X7R,-,2012	
C19C	2203-005171	C-CER,CHIP;1000nF,10%,16V,X7R,-,2012	
C20S	2203-005171	C-CER,CHIP;1000nF,10%,16V,X7R,-,2012	
C20RR	2203-005171	C-CER,CHIP;1000nF,10%,16V,X7R,-,2012	
C20RL	2203-005171	C-CER,CHIP;1000nF,10%,16V,X7R,-,2012	
C20C	2203-005171	C-CER,CHIP;1000nF,10%,16V,X7R,-,2012	
C20FL	2203-005171	C-CER,CHIP;1000nF,10%,16V,X7R,-,2012	
C20FR	2203-005171	C-CER,CHIP;1000nF,10%,16V,X7R,-,2012	
C24	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608,-	
C25	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608,-	
C26	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608,-	
C4	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608,-	
C4C	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608,-	
C4FL	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608,-	
C4FR	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608,-	
C23	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608,-	
C17C	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608,-	
C17FL	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608,-	
C17FR	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608,-	
C17RL	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608,-	
C17RR	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608,-	
C17S	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608,-	
C2	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608,-	
C4RL	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608,-	
C7S	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608,-	
C9C	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608,-	
C9FL	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608,-	
C9FR	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608,-	
C9RL	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608,-	
C9RR	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608,-	
C9S	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608,-	
C7RR	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608,-	
C4RR	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608,-	
C4S	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608,-	
C5	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608,-	
C7C	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608,-	
C7FL	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608,-	
C7FR	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608,-	

Location no.	Code no.	Description & Specification	Remarks
C7RL	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608,-	
C143	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608,-	
C144	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608,-	
C145	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608,-	
C146	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608,-	
C147	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608,-	
C148	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608,-	
C149	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608,-	
C141	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608,-	
C11C	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608,-	
C11FL	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608,-	
C11FR	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608,-	
C11RL	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608,-	
C11RR	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608,-	
C11S	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608,-	
C140	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608,-	
C150	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608,-	
C15FR	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608,-	
C15RL	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608,-	
C15RR	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608,-	
C15S	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608,-	
C174	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608,-	
C175	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608,-	
C177	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608,-	
C15FL	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608,-	
C151	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608,-	
C152	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608,-	
C153	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608,-	
C154	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608,-	
C155	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608,-	
C156	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608,-	
C15C	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608,-	
C27	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608,-	
C10S	2305-000412	C-FILM,LEAD-PEF;470nF,5%,63V,TP,-,5mm	
C10RR	2305-000412	C-FILM,LEAD-PEF;470nF,5%,63V,TP,-,5mm	
C10RL	2305-000412	C-FILM,LEAD-PEF;470nF,5%,63V,TP,-,5mm	
C10C	2305-000412	C-FILM,LEAD-PEF;470nF,5%,63V,TP,-,5mm	
C10FL	2305-000412	C-FILM,LEAD-PEF;470nF,5%,63V,TP,-,5mm	
C10FR	2305-000412	C-FILM,LEAD-PEF;470nF,5%,63V,TP,-,5mm	
C1	2401-000240	C-AL;100uF,20%,10V,GP,TP,5x11,5	
C8	2401-000303	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
C3	2401-000438	C-AL;10UF,20%,25V,GP,-,5X11,5	
C139	2401-000438	C-AL;10UF,20%,25V,GP,-,5X11,5	
SC4L	2401-000459	C-AL;10uF,20%,35V,GP,TP,5.5x7mm,5mm	
SC4R	2401-000459	C-AL;10uF,20%,35V,GP,TP,5.5x7mm,5mm	
SC5L	2401-000459	C-AL;10uF,20%,35V,GP,TP,5.5x7mm,5mm	
SC5R	2401-000459	C-AL;10uF,20%,35V,GP,TP,5.5x7mm,5mm	
HC5R	2401-000459	C-AL;10uF,20%,35V,GP,TP,5.5x7mm,5mm	
HC5L	2401-000459	C-AL;10uF,20%,35V,GP,TP,5.5x7mm,5mm	
HC4R	2401-000459	C-AL;10uF,20%,35V,GP,TP,5.5x7mm,5mm	
HC4L	2401-000459	C-AL;10uF,20%,35V,GP,TP,5.5x7mm,5mm	
C22	2401-001022	C-AL;3.3UF,20%,50V,GP,TP,5X11,5	
C138	2401-001355	C-AL;470uF,20%,10V,GP,TP,8x11.5mm,5	
C137	2401-001355	C-AL;470uF,20%,10V,GP,TP,8x11.5mm,5	
C136	2401-001355	C-AL;470uF,20%,10V,GP,TP,8x11.5mm,5	
C135	2401-001355	C-AL;470uF,20%,10V,GP,TP,8x11.5mm,5	
C178	2401-001364	C-AL;470uF,20%,16V,GP,TP,10x12.5,5	
FC1	2401-001538	C-AL;47uF,20%,25V,GP,TP,5x11mm,5mm	
SC8R	2401-001893	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
SC8L	2401-001893	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
HC8R	2401-001893	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
HC8L	2401-001893	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
SC2	2401-001975	C-AL;47uF,20%,16V,GP,TP,5x11mm,5mm	
SC1	2401-001975	C-AL;47uF,20%,16V,GP,TP,5x11mm,5mm	
HC2	2401-001975	C-AL;47uF,20%,16V,GP,TP,5x11mm,5mm	
HC1	2401-001975	C-AL;47uF,20%,16V,GP,TP,5x11mm,5mm	
SL1R	2703-000404	INDUCTOR-SMD;220uH,10%,3225	
SL1L	2703-000404	INDUCTOR-SMD;220uH,10%,3225	
HL1R	2703-000404	INDUCTOR-SMD;220uH,10%,3225	
HL1L	2703-000404	INDUCTOR-SMD;220uH,10%,3225	
FB4	3301-001069	BEAD-SMD;120ohm,1.6x0.8x0.8mm,200mA,TP,	
FB3	3301-001069	BEAD-SMD;120ohm,1.6x0.8x0.8mm,200mA,TP,	
FB2	3301-001069	BEAD-SMD;120ohm,1.6x0.8x0.8mm,200mA,TP,	
FB1	3301-001069	BEAD-SMD;120ohm,1.6x0.8x0.8mm,200mA,TP,	